

Error-Erasure Decoding of Linearized Reed–Solomon Codes in the Sum-Rank Metric

Felicitas Hörmann, Hannes Bartz
Institute of Communications and Navigation
German Aerospace Center (DLR)
 Oberpfaffenhofen, Germany
 {felicitas.hoermann, hannes.bartz}@dlr.de

Sven Puchinger
Hensoldt Sensors GmbH
 Ulm, Germany
 sven.puchinger@tum.de

Abstract—Codes in the sum-rank metric have various applications in error control for multishot network coding, distributed storage and code-based cryptography. Linearized Reed–Solomon (LRS) codes contain Reed–Solomon and Gabidulin codes as subclasses and fulfill the Singleton-like bound in the sum-rank metric with equality. We propose the first known error-erasure decoder for LRS codes to unleash their full potential for multishot network coding by incorporating erasures into the known syndrome-based Berlekamp–Massey-like decoder. This allows to correct t_F full errors, t_R row erasures and t_C column erasures up to $2t_F + t_R + t_C \leq n - k$ in the sum-rank metric requiring at most $\mathcal{O}(n^2)$ operations in \mathbb{F}_{q^m} , where n is the code’s length and k its dimension. We show how the proposed decoder can be used to correct errors in the sum-subspace metric that occur in (noncoherent) multishot network coding.

Index Terms—error-erasure decoding, linearized Reed–Solomon codes, sum-rank metric, syndrome-based decoding

I. INTRODUCTION

The sum-rank metric is a generalization of both the Hamming and the rank metric and was first considered in [1, Sec. III] for designing space-time codes. Later, Nóbrega and Uchôa-Filho showed that the sum-rank metric is suitable for error control in *coherent* multishot network coding and proposed a multilevel code construction [2]. Other constructions of codes in the sum-rank metric include partial unit memory codes constructed from rank-metric codes [3], [4], convolutional codes [5], [6] and variable block-size constructions [7].

Martínez-Peñas introduced linearized Reed–Solomon (LRS) codes which include Reed–Solomon and Gabidulin codes as special cases [8]. LRS codes fulfill the Singleton-like bound in the sum-rank metric with equality and thus are maximum sum-rank distance (MSRD) codes. The interest in LRS and other sum-rank metric codes keeps increasing as they have multiple widespread applications as e.g. multishot network coding [2], [9], locally repairable codes [10], space-time codes [1] and code-based quantum-resistant cryptography [11]. Recently, it was shown that *interleaved* [12], [13] and *folded* [14] variants

of LRS codes can be decoded beyond the unique decoding radius. The concept of row and column erasures, i.e. the partial knowledge of the column and row space of the error, respectively, was generalized from the rank metric [15] to the sum-rank metric in [11].

In this paper, we extend the syndrome-based error-only decoder for LRS codes from [16] to a Berlekamp–Massey-like error-erasure decoder that can correct t_F full errors, t_R row and t_C column erasures as long as $2t_F + t_R + t_C \leq n - k$ requiring $\mathcal{O}(n^2)$ operations in \mathbb{F}_{q^m} , where n denotes the length and k the dimension of the code, respectively. The proposed algorithm is inspired by the error-erasure decoding algorithms for Gabidulin codes from [17], [18]. Further, we show how the results can be used to decode lifted LRS codes for error control in multishot network coding [19].

Up to our knowledge, the proposed decoder is the first decoding scheme for LRS codes that is capable of correcting both errors and row/column erasures in the sum-rank metric.

II. NOTATION AND PRELIMINARIES

For a prime power q and a positive integer m , let \mathbb{F}_q denote a finite field of order q and $\mathbb{F}_{q^m} \supseteq \mathbb{F}_q$ its extension field with extension degree m . Under a fixed basis of \mathbb{F}_{q^m} over \mathbb{F}_q there is a bijection between any element $a \in \mathbb{F}_{q^m}$ and a length- m column vector \mathbf{a} over \mathbb{F}_q . Recall further that an element $\gamma \in \mathbb{F}_{q^m}$ is called *primitive* in \mathbb{F}_{q^m} if it generates $\mathbb{F}_{q^m}^* := \mathbb{F}_{q^m} \setminus \{0\}$.

Consider an automorphism $\theta : \mathbb{F}_{q^m} \rightarrow \mathbb{F}_{q^m}$. Two elements $a, b \in \mathbb{F}_{q^m}$ are called θ -conjugate, if there exists an element $c \in \mathbb{F}_{q^m}^*$ such that $b = \theta(c)ac^{-1}$. The *conjugacy class* $\mathcal{C}(a)$ is the set of all θ -conjugates of a and $\mathcal{C}(0)$ is called trivial conjugacy class. Note that θ -conjugacy defines an equivalence relation on \mathbb{F}_{q^m} and that the conjugacy classes form a partition of \mathbb{F}_{q^m} (see e.g. [20]). Let $\{\xi_1, \dots, \xi_\ell\} \subseteq \mathbb{F}_{q^m}^*$ be a set of representatives of distinct nontrivial conjugacy classes of \mathbb{F}_{q^m} . Then, $\mathcal{C}(\theta(\xi_1)), \dots, \mathcal{C}(\theta(\xi_\ell))$ as well as $\mathcal{C}(\theta^{-1}(\xi_1^{-1})), \dots, \mathcal{C}(\theta^{-1}(\xi_\ell^{-1}))$ are distinct and nontrivial classes because they are injective images of $\mathcal{C}(\xi_1), \dots, \mathcal{C}(\xi_\ell)$.

A. Skew Polynomials

For an automorphism θ on \mathbb{F}_{q^m} , the non-commutative *skew polynomial ring* $\mathbb{F}_{q^m}[x; \theta]$ (with zero derivation) consists of all formal polynomials $\sum_i f_i x^{i-1}$ having finitely many nonzero coefficients $f_i \in \mathbb{F}_{q^m}$. It is equipped with ordinary polynomial

This work was done while S. Puchinger was with the Department of Applied Mathematics and Computer Science, Technical University of Denmark (DTU), Lyngby, Denmark and the Department of Electrical and Computer Engineering, Technical University of Munich, Munich, Germany. Within this period he was supported by the European Union’s Horizon 2020 research and innovation program under the Marie Skłodowska-Curie grant agreement no. 713683 and by the European Research Council (ERC) under the European Union’s Horizon 2020 research and innovation programme (grant agreement no. 801434).

addition and the multiplication is determined by $xf_i = \theta(f_i)x$ for all $f_i \in \mathbb{F}_{q^m}$. Naturally, the *degree* of a nonzero skew polynomial $f(x) = \sum_i f_i x^{i-1}$ is $\deg(f) := \max\{i : f_{i+1} \neq 0\}$ whereas the degree of the zero polynomial is set to $-\infty$. We use the notation $\mathbb{F}_{q^m}[x; \theta]_{<k} := \{f \in \mathbb{F}_{q^m}[x; \theta] : \deg(f) < k\}$ for any $k \geq 0$.

Note that $\mathbb{F}_{q^m}[x; \theta]$ is a left and right Euclidean ring which ensures the existence of $q_l, r_l, q_r, r_r \in \mathbb{F}_{q^m}[x; \theta]$ such that

$$a = q_l b + r_l \quad \text{with } \deg(r_l) < \deg(b) \quad (1)$$

$$\text{and } a = b q_r + r_r \quad \text{with } \deg(r_r) < \deg(b) \quad (2)$$

for every $a, b \in \mathbb{F}_{q^m}[x; \theta]$. We write $r_l = a \bmod_l b$ and $r_r = a \bmod_r b$, respectively.

The product $p = f \cdot g \in \mathbb{F}_{q^m}[x; \theta]$ of two skew polynomials $f, g \in \mathbb{F}_{q^m}[x; \theta]$ with $d_f := \deg(f)$ and $d_g := \deg(g)$ has degree $d_f + d_g$. The coefficients p_l of p with $\min(d_f, d_g) + 1 \leq l \leq \max(d_f, d_g) + 1$ can be computed as (see [21])

$$p_l = \sum_{i=1}^{d_f+1} f_i \theta^{i-1}(g_{l-i+1}) \quad \text{if } d_f \leq d_g \quad (3)$$

$$\text{and } p_l = \sum_{i=1}^{d_g+1} f_{l-i+1} \theta^{l-i}(g_i) \quad \text{if } d_g \leq d_f. \quad (4)$$

The (partial) θ -reverse of f with respect to an integer $t \geq d_f$ is defined as $\bar{f}(x) = \sum_{i=1}^{t+1} \bar{f}_i x^{i-1}$, where $\bar{f}_i = \theta^{i-t-1}(f_{t-i+2})$ for all $i = 1, \dots, t+1$ [21, p. 574], [18, Sec. 2.4].

For all $a \in \mathbb{F}_{q^m}$, the *generalized power function* is defined as $\mathcal{N}_\theta^0(a) = 1$ and as $\mathcal{N}_\theta^i(a) = \theta^{i-1}(a) \cdot \mathcal{N}_\theta^{i-1}(a)$ for all $i > 0$ (see [20]). This notion is used to define the operator

$$\mathcal{D}_{\theta,a}(b) := \theta(b)a \quad \text{for all } a, b \in \mathbb{F}_{q^m} \quad (5)$$

and for all $i \in \mathbb{N}$ and $a, b \in \mathbb{F}_{q^m}$ its powers (see [8, Prop. 32])

$$\mathcal{D}_{\theta,a}^i(b) = \mathcal{D}_{\theta,a}(\mathcal{D}_{\theta,a}^{i-1}(b)) = \theta^i(b) \mathcal{N}_\theta^i(a). \quad (6)$$

A vector $\mathbf{n} := (n_1, \dots, n_\ell) \in \mathbb{N}^\ell$ is called a *length partition* of $n \in \mathbb{N}$ if $n = \sum_{i=1}^\ell n_i$. We divide $\mathbf{x} \in \mathbb{F}_{q^m}^n$ into ℓ blocks with respect to \mathbf{n} by writing $\mathbf{x} = (\mathbf{x}^{(1)} \mid \dots \mid \mathbf{x}^{(\ell)})$ with $\mathbf{x}^{(i)} \in \mathbb{F}_{q^m}^{n_i}$. For a fixed ordered \mathbb{F}_q -basis of \mathbb{F}_{q^m} there are isomorphisms $\mathbb{F}_{q^m}^{n_i} \rightarrow \mathbb{F}_q^{m \times n_i}$ which allow to define the \mathbb{F}_q -rank of each vector $\mathbf{x}^{(i)}$, i.e. $\text{rk}_{\mathbb{F}_q}(\mathbf{x}^{(i)})$, as the rank of the corresponding matrix. The *generalized Moore matrix* for \mathbf{x} , a vector $\mathbf{a} = (a_1, \dots, a_\ell) \in \mathbb{F}_{q^m}^\ell$ and a parameter $d \in \mathbb{N}^*$ is defined as

$$\mathfrak{M}_\theta^d(\mathbf{x})_{\mathbf{a}} := (\mathbf{V}_\theta^d(\mathbf{x}^{(1)})_{a_1} \quad \dots \quad \mathbf{V}_\theta^d(\mathbf{x}^{(\ell)})_{a_\ell}) \in \mathbb{F}_{q^m}^{d \times n} \quad (7)$$

where its Vandermonde-like submatrices $\mathbf{V}_\theta^d(\mathbf{x}^{(i)})_{a_i}$ are

$$\mathbf{V}_\theta^d(\mathbf{x}^{(i)})_{a_i} := \begin{pmatrix} x_1^{(i)} & \dots & x_{n_i}^{(i)} \\ \mathcal{D}_{\theta,a_i}(x_1^{(i)}) & \dots & \mathcal{D}_{\theta,a_i}(x_{n_i}^{(i)}) \\ \vdots & \ddots & \vdots \\ \mathcal{D}_{\theta,a_i}^{d-1}(x_1^{(i)}) & \dots & \mathcal{D}_{\theta,a_i}^{d-1}(x_{n_i}^{(i)}) \end{pmatrix} \quad (8)$$

for $1 \leq i \leq \ell$. If \mathbf{a} contains representatives of pairwise distinct nontrivial conjugacy classes of \mathbb{F}_{q^m} and $\text{rk}_{\mathbb{F}_q}(\mathbf{x}^{(i)}) = n_i$ for all $1 \leq i \leq \ell$, we have by [8, Thm. 2] and [20, Thm. 4.5] that $\text{rk}_{\mathbb{F}_{q^m}}(\mathfrak{M}_\theta^d(\mathbf{x})_{\mathbf{a}}) = \min(d, n)$.

The *generalized operator evaluation* of a skew polynomial

$f \in \mathbb{F}_{q^m}[x; \theta]$ at an element $b \in \mathbb{F}_{q^m}$ with respect to an evaluation parameter $a \in \mathbb{F}_{q^m}$ is defined as (see [8], [22])

$$f(b)_a = \sum_i f_i \mathcal{D}_{\theta,a}^{i-1}(b). \quad (9)$$

For a fixed evaluation parameter a the generalized operator evaluation forms an \mathbb{F}_q -linear map [22]. The evaluation of a product of two skew polynomials $f, g \in \mathbb{F}_{q^m}[x; \theta]$ satisfies $(f \cdot g)(b)_a = f(g(b)_a)_a$ for all $a, b \in \mathbb{F}_{q^m}$ [23].

The *minimal (skew) polynomial* that vanishes on the set $\{b_1^{(i)}, \dots, b_{n_i}^{(i)}\} \subseteq \mathbb{F}_{q^m}$ with respect to the evaluation parameter $a_i \in \mathbb{F}_{q^m}$ for all $i = 1, \dots, \ell$ is defined as

$$\text{mpol}_{\{a_i\}_{i=1}^\ell}^{\{b_\kappa^{(i)}\}_{\kappa=1}^{n_i}}(b_\kappa^{(i)})_{a_i} = 0 \quad \text{for all } \begin{matrix} 1 \leq \kappa \leq n_i \\ 1 \leq i \leq \ell \end{matrix}. \quad (10)$$

When assuming $b_\kappa^{(i)} \neq 0$ for all indices it can be computed as

$$\text{mpol}_{\{a_i\}_{i=1}^\ell}^{\{b_\kappa^{(i)}\}_{\kappa=1}^{n_i}}(x) = \text{lclm} \left(x - \frac{\theta(b_\kappa^{(i)})_{a_i}}{b_\kappa^{(i)}} \right)_{\substack{1 \leq \kappa \leq n_i \\ 1 \leq i \leq \ell}} \quad (11)$$

where $\text{lclm}(\cdot)$ denotes the least common left multiple of the polynomials in the bracket [24, Sec. 1.3.1]. Its degree is at most $\sum_{i=1}^\ell n_i$ and equality holds if and only if the $b_\kappa^{(i)}$ belonging to the same evaluation parameter a_i are \mathbb{F}_q -linearly independent and the evaluation parameters a_i are representatives of different nontrivial conjugacy classes of \mathbb{F}_{q^m} .

B. Sum-Rank Metric and Linearized Reed–Solomon Codes

The *sum-rank weight* of a vector $\mathbf{x} \in \mathbb{F}_{q^m}^n$ with respect to the length partition $\mathbf{n} \in \mathbb{N}^\ell$ is

$$\text{wt}_{\Sigma R}^{\mathbf{n}}(\mathbf{x}) = \sum_{i=1}^\ell \text{rk}_{\mathbb{F}_q}(\mathbf{x}^{(i)}). \quad (12)$$

The metric introduced by $d_{\Sigma R}^{\mathbf{n}}(\mathbf{x}, \mathbf{y}) := \text{wt}_{\Sigma R}^{\mathbf{n}}(\mathbf{x} - \mathbf{y})$ for all $\mathbf{x}, \mathbf{y} \in \mathbb{F}_{q^m}^n$ is called the *sum-rank metric* (with respect to \mathbf{n}). When \mathbf{n} is clear from the context, we simply write $\text{wt}_{\Sigma R}$ and $d_{\Sigma R}$, respectively.

An $[n, k]$ *linear sum-rank metric code* $\mathcal{C} \subseteq \mathbb{F}_{q^m}^n$ is defined as a k -dimensional \mathbb{F}_{q^m} -linear subspace of $\mathbb{F}_{q^m}^n$ and thus has length n . Its *minimum sum-rank distance* is

$$d_{\Sigma R}(\mathcal{C}) := \min_{\substack{\mathbf{x}, \mathbf{y} \in \mathcal{C}, \\ \mathbf{x} \neq \mathbf{y}}} \{d_{\Sigma R}(\mathbf{x}, \mathbf{y})\} = \min_{\substack{\mathbf{x} \in \mathcal{C}, \\ \mathbf{x} \neq \mathbf{0}}} \{\text{wt}_{\Sigma R}(\mathbf{x})\}, \quad (13)$$

where the last equality follows by linearity. Codes achieving the Singleton-like bound $d_{\Sigma R}(\mathcal{C}) \leq n - k + 1$ (see e.g. [8, Prop. 34]) with equality are called *maximum sum-rank distance (MSRD) codes*.

Definition 1 (Linearized Reed–Solomon Codes): Let $\boldsymbol{\xi} = (\xi_1, \dots, \xi_\ell) \in \mathbb{F}_{q^m}^\ell$ be a vector containing representatives of pairwise distinct nontrivial conjugacy classes of \mathbb{F}_{q^m} and consider a length partition $\mathbf{n} := (n_1, \dots, n_\ell) \in \mathbb{N}^\ell$ of $n \in \mathbb{N}$. Let the vectors $\boldsymbol{\beta}^{(i)} = (\beta_1^{(i)}, \dots, \beta_{n_i}^{(i)}) \in \mathbb{F}_{q^m}^{n_i}$ contain \mathbb{F}_q -linearly independent elements of \mathbb{F}_{q^m} for all $i = 1, \dots, \ell$ and define $\boldsymbol{\beta} := (\boldsymbol{\beta}^{(1)} \mid \dots \mid \boldsymbol{\beta}^{(\ell)}) \in \mathbb{F}_{q^m}^n$. A *linearized Reed–Solomon (LRS) code* $\text{LRS}[\theta, \boldsymbol{\beta}, \boldsymbol{\xi}, \ell; \mathbf{n}, k] \subseteq \mathbb{F}_{q^m}^n$ of length n and dimension k is defined as

$$\left\{ \left(f(\boldsymbol{\beta}^{(1)})_{\xi_1} \mid \dots \mid f(\boldsymbol{\beta}^{(\ell)})_{\xi_\ell} \right) : f \in \mathbb{F}_{q^m}[x; \theta]_{<k} \right\} \quad (14)$$

where $f(\beta^{(i)})_{\xi_i} := (f(\beta_1^{(i)})_{\xi_i}, \dots, f(\beta_{n_i}^{(i)})_{\xi_i})$ for $1 \leq i \leq \ell$.

LRS codes have minimum sum-rank distance $n - k + 1$ and are thus MSRD [8, Thm. 4]. Furthermore, $\text{LRS}[\theta, \beta, \xi, \ell; \mathbf{n}, k]$ has a generator matrix of the form $\mathbf{G} = \mathfrak{M}_\theta^k(\beta)_\xi$ [8, Sec. 3.3].

The dual of an LRS code can be described as (see [24], [25])

$$\text{LRS}[\theta, \beta, \xi, \ell; \mathbf{n}, k]^\perp = \text{LRS}[\theta^{-1}, \alpha, \theta^{-1}(\xi), \ell; \mathbf{n}, n-k] \quad (15)$$

where the vector $\alpha = (\alpha^{(1)} \mid \dots \mid \alpha^{(\ell)}) \in \mathbb{F}_{q^m}^n$ (with $\alpha^{(i)} = (\alpha_1^{(i)}, \dots, \alpha_{n_i}^{(i)}) \in \mathbb{F}_{q^m}^{n_i}$ for $i = 1, \dots, \ell$) satisfies

$$\sum_{i=1}^{\ell} \sum_{\kappa=1}^{n_i} \alpha_\kappa^{(i)} \mathcal{D}_{\theta, \xi_i}^{l-1}(\beta_\kappa^{(i)}) = 0 \quad \text{for all } l = 1, \dots, n-1 \quad (16)$$

and has sum-rank weight $\text{wt}_{\Sigma R}(\alpha) = n$ (see [9, Thm. 4]). Hence, there exists a parity-check matrix of $\text{LRS}[\theta, \beta, \xi, \ell; \mathbf{n}, k]$ of the form $\mathbf{H} = \mathfrak{M}_{\theta^{-1}}^{n-k}(\alpha)_{\theta^{-1}(\xi)}$.

III. ERROR-ERASURE DECODING

A. Channel Model

We consider an additive sum-rank channel with fixed error weight $\tau \in \mathbb{N}$ and incorporate three types of errors. Next to t_F conventional (full) errors, we allow t_R row erasures whose column spaces are known and t_C column erasures whose row spaces are given by the channel. Erasures and the notions of row and column support in the sum-rank metric have already been studied in [11] and naturally generalize the respective rank-metric concepts (see e.g. [15], [19], [26]).

The error vector $e = (e^{(1)} \mid \dots \mid e^{(\ell)}) \in \mathbb{F}_{q^m}^n$ is assumed to have sum-rank weight $\text{wt}_{\Sigma R}(e) = \tau = t_F + t_R + t_C$. To emphasize in which block the errors occurred, we write $\tau^{(i)} = \text{rk}_{\mathbb{F}_q}(e^{(i)}) = t_F^{(i)} + t_R^{(i)} + t_C^{(i)}$ for all $i = 1, \dots, \ell$. In this context, the transmission of a codeword $c \in \text{LRS}[\theta, \beta, \xi, \ell; \mathbf{n}, k]$ yields a channel observation $y \in \mathbb{F}_{q^m}^n$ of the form $y = c + e$.

We have already implicitly assumed that e has an additive decomposition $e = e_F + e_R + e_C$ with respect to the considered error types, where $e_T \in \mathbb{F}_{q^m}^n$ satisfies $\text{wt}_{\Sigma R}(e_T) = t_T$ for all $T \in \{F, R, C\}$. Application of [11, Lem. 5] leads for all error types $T \in \{F, R, C\}$ to a representation

$$e_T = \underbrace{(\mathbf{a}_T^{(1)} \mid \dots \mid \mathbf{a}_T^{(\ell)})}_{=: \mathbf{a}_T \in \mathbb{F}_{q^m}^{t_T}} \cdot \underbrace{\begin{pmatrix} \mathbf{B}_T^{(1)} & & \\ & \ddots & \\ & & \mathbf{B}_T^{(\ell)} \end{pmatrix}}_{=: \mathbf{B}_T \in \mathbb{F}_q^{t_T \times n}} \quad (17)$$

where both $\mathbf{a}_T^{(i)} \in \mathbb{F}_{q^m}^{t_T^{(i)}}$ and $\mathbf{B}_T^{(i)} \in \mathbb{F}_q^{t_T^{(i)} \times n_i}$ have rank $t_T^{(i)}$ for all $i = 1, \dots, \ell$. Note that the entries of $\mathbf{a}_T^{(i)}$ form a basis of the column space of $e_T^{(i)}$ and the rows of $\mathbf{B}_T^{(i)} = (b_{T,j,\kappa}^{(i)})_{j,\kappa}$ are a basis of its row space. Hence, according to the definition of row and column erasures, \mathbf{a}_R and \mathbf{B}_C are known to the receiver.

We define the error locators corresponding to the i -th block of e for each $i = 1, \dots, \ell$ as the $\tau^{(i)}$ components of the vector $\mathbf{x}^{(i)} = (\mathbf{x}_F^{(i)}, \mathbf{x}_R^{(i)}, \mathbf{x}_C^{(i)}) \in \mathbb{F}_{q^m}^{\tau^{(i)}}$, where $\mathbf{x}_T^{(i)} \in \mathbb{F}_{q^m}^{t_T^{(i)}}$ with $T \in \{F, R, C\}$ has the entries

$$x_{T,j}^{(i)} := \sum_{\kappa=1}^{n_i} b_{T,j,\kappa}^{(i)} \alpha_\kappa^{(i)} \quad \text{for all } j = 1, \dots, t_T^{(i)}. \quad (18)$$

For simplicity we renumber the entries of $\mathbf{x}^{(i)}$ and reference them as $x_r^{(i)}$ for $1 \leq r \leq \tau^{(i)}$ and $1 \leq i \leq \ell$ in the following. Similarly we write $\mathbf{a}^{(i)} = (\mathbf{a}_F^{(i)}, \mathbf{a}_R^{(i)}, \mathbf{a}_C^{(i)}) \in \mathbb{F}_{q^m}^{\tau^{(i)}}$ for the vector containing the error values of the i -th error block and $a_r^{(i)}$ for its entries (for $r = 1, \dots, \tau^{(i)}$ and $i = 1, \dots, \ell$).

Now consider the syndrome $\mathbf{s} = \mathbf{y}\mathbf{H}^\top = \mathbf{e}\mathbf{H}^\top$. Then, the entries of \mathbf{s} can be written as

$$s_l = \sum_{i=1}^{\ell} \sum_{r=1}^{\tau^{(i)}} a_r^{(i)} \mathcal{D}_{\theta^{-1}, \theta^{-1}(\xi_i)}^{l-1}(x_r^{(i)}) \quad (19)$$

for all $l = 1, \dots, n-k$. When letting $\mathbf{x} = (\mathbf{x}^{(1)} \mid \dots \mid \mathbf{x}^{(\ell)})$ and $\mathbf{a} = (\mathbf{a}^{(1)} \mid \dots \mid \mathbf{a}^{(\ell)})$ denote the vectors containing all error locators and all error values, respectively, we have the equivalent formulation (see also [11])

$$\mathbf{X}\mathbf{a}^\top = \mathbf{s}^\top \quad \text{with } \mathbf{X} = \mathfrak{M}_{\theta^{-1}}^{n-k}(\mathbf{x})_{\theta^{-1}(\xi)} \in \mathbb{F}_{q^m}^{(n-k) \times \tau} \quad (20)$$

where $\theta^{-1}(\xi)$ is defined as $(\theta^{-1}(\xi_1), \dots, \theta^{-1}(\xi_\ell))$.

By applying θ^{l-1} to (19) we get

$$\theta^{l-1}(s_l) = \sum_{i=1}^{\ell} \sum_{r=1}^{\tau^{(i)}} x_r^{(i)} \mathcal{D}_{\theta, \xi_i}^{l-1}(a_r^{(i)}) \quad (21)$$

for all $l = 1, \dots, n-k$ and equivalently

$$\mathbf{A}\mathbf{x}^\top = \tilde{\mathbf{s}}^\top \quad \text{with } \mathbf{A} = \mathfrak{M}_\theta^{n-k}(\mathbf{a})_\xi \in \mathbb{F}_{q^m}^{(n-k) \times \tau} \quad (22)$$

and $\tilde{\mathbf{s}} = (s_1, \theta(s_2), \dots, \theta^{n-k-1}(s_{n-k})) \in \mathbb{F}_{q^m}^{n-k}$.

B. ESP and ELP Key Equation

We can now define the error span polynomial (ESP) $\sigma \in \mathbb{F}_{q^m}[x; \theta^{-1}]$ as the minimal polynomial

$$\sigma(x) = \sum_{\nu=1}^{\tau+1} \sigma_\nu x^{\nu-1} \quad \text{with } \sigma(a_r^{(i)})_{\theta^{-1}(\xi_i^{-1})} = 0 \quad (23)$$

for all $r = 1, \dots, \tau^{(i)}$ and all $i = 1, \dots, \ell$. In an analogous manner the error locator polynomial (ELP) $\lambda \in \mathbb{F}_{q^m}[x; \theta^{-1}]$ is the minimal polynomial

$$\lambda(x) = \sum_{\nu=1}^{\tau+1} \lambda_\nu x^{\nu-1} \quad \text{with } \lambda(x_r^{(i)})_{\theta^{-1}(\xi_i)} = 0 \quad (24)$$

for every $r = 1, \dots, \tau^{(i)}$ and $i = 1, \dots, \ell$. Note that both σ and λ are members of a skew polynomial ring with respect to the inverse automorphism θ^{-1} and we consider generalized operator evaluation parameters that are different compared to the LRS code construction.

Let us now express the ESP and the ELP as products of three polynomials related to the different error types. This will prove beneficial for incorporating the knowledge about row and column erasures into the decoder. We write

$$\sigma(x) = \sigma_C(x) \cdot \sigma_F(x) \cdot \sigma_R(x) \quad (25)$$

$$\text{and } \lambda(x) = \lambda_R(x) \cdot \lambda_F(x) \cdot \lambda_C(x) \quad (26)$$

where the partial ESPs $\sigma_F, \sigma_R, \sigma_C \in \mathbb{F}_{q^m}[x; \theta^{-1}]$ are defined as $\sigma_T(x) = \sum_{\nu=1}^{t_T+1} \sigma_{T,\nu} x^{\nu-1}$ for $T \in \{F, R, C\}$ being the minimal polynomials satisfying

$$(\sigma_C \cdot \sigma_F \cdot \sigma_R)(a_{C,j}^{(i)})_{\theta^{-1}(\xi_i^{-1})} = 0 \quad \text{for } j = 1, \dots, t_C^{(i)},$$

$$(\sigma_F \cdot \sigma_R)(a_{F,j}^{(i)})_{\theta^{-1}(\xi_i^{-1})} = 0 \quad \text{for } j = 1, \dots, t_F^{(i)}, \quad (27)$$

$$\text{and } \sigma_R(a_{R,j}^{(i)})_{\theta^{-1}(\xi_i^{-1})} = 0 \quad \text{for } j = 1, \dots, t_R^{(i)}$$

for all $i = 1, \dots, \ell$, respectively. Similarly, the partial error locator polynomials $\lambda_F, \lambda_R, \lambda_C \in \mathbb{F}_{q^m}[x; \theta^{-1}]$ with $\lambda_T(x) = \sum_{\nu=1}^{t_T+1} \lambda_{T,\nu} x^{\nu-1}$ for $T \in \{F, R, C\}$ are given as the minimal polynomials that satisfy

$$\begin{aligned} (\lambda_R \cdot \lambda_F \cdot \lambda_C)(x_{R,j}^{(i)})_{\theta^{-1}(\xi_i)} &= 0 \quad \text{for } j = 1, \dots, t_R^{(i)}, \\ (\lambda_F \cdot \lambda_C)(x_{F,j}^{(i)})_{\theta^{-1}(\xi_i)} &= 0 \quad \text{for } j = 1, \dots, t_F^{(i)}, \quad (28) \\ \text{and } \lambda_C(x_{C,j}^{(i)})_{\theta^{-1}(\xi_i)} &= 0 \quad \text{for } j = 1, \dots, t_C^{(i)} \end{aligned}$$

for all $1 \leq i \leq \ell$, respectively. Note that since \mathbf{a}_R and \mathbf{B}_C are known, we can compute σ_R and λ_C using (11).

Let $s \in \mathbb{F}_{q^m}[x; \theta^{-1}]$ be the *syndrome polynomial* that is obtained from the syndrome $\mathbf{s} = (s_1, \dots, s_{n-k})$ as

$$s(x) = \sum_{l=1}^{n-k} s_l x^{l-1}. \quad (29)$$

Consider the auxiliary syndrome polynomial

$$s_{RC}(x) := \sigma_R(x) \cdot s(x) \cdot \overline{\lambda_C}(x) \in \mathbb{F}_{q^m}[x; \theta^{-1}] \quad (30)$$

where $\overline{\lambda_C}$ denotes the θ^{-1} -reverse of λ_C with respect to t_C . This allows to derive the ESP key equation that is the main ingredient of (the ESP variant of) our error-erasure decoder.

Theorem 1 (ESP Key Equation): There is a skew polynomial $\omega \in \mathbb{F}_{q^m}[x; \theta^{-1}]$ of degree less than $\tau = t_F + t_R + t_C$ such that

$$\sigma_F(x) \cdot s_{RC}(x) \equiv \omega(x) \pmod{x^{n-k}}. \quad (31)$$

Proof: Let us write $\sigma_{FR} := \sigma_F \cdot \sigma_R$ as well as $\tilde{\xi}_i := \theta^{-1}(\xi_i)$ and $\hat{\xi}_i := \theta^{-1}(\xi_i^{-1})$ ($i = 1, \dots, \ell$) for brevity. For $t_F + t_R + 1 \leq l \leq n - k$ the l -th coefficient of $\sigma_F \cdot \sigma_R \cdot s$ is

$$\begin{aligned} (\sigma_F \cdot \sigma_R \cdot s)_l &= \sum_{\nu=1}^{t_F+t_R+1} \sigma_{FR,\nu} \theta^{-(\nu-1)} (s_{l-\nu+1}) \\ &= \sum_{i=1}^{\ell} \sum_{r=1}^{\tau^{(i)}} \sigma_{FR}(a_r^{(i)})_{\hat{\xi}_i} \mathcal{D}_{\theta^{-1}, \hat{\xi}_i}^{l-1}(x_r^{(i)}). \quad (32) \end{aligned}$$

For $t_C + 1 \leq l \leq t_F + t_R + n - k$ we have

$$\begin{aligned} (\sigma_F \cdot \sigma_R \cdot s \cdot \overline{\lambda_C})_l &= \sum_{\nu=1}^{t_C+1} (\sigma_{FR} \cdot s)_{l-\nu+1} \theta^{-(l-\nu)} (\overline{\lambda_C})_{\nu} \\ &= \sum_{i=1}^{\ell} \sum_{r=1}^{\tau^{(i)}} \sigma_{FR}(a_r^{(i)})_{\hat{\xi}_i} \theta^{-(l-t_C-1)} (\mathcal{N}_{\theta}^{l-t_C-1}(\xi_i)) \cdot \theta^{-(l-t_C-1)} \left(\sum_{\nu=1}^{t_C+1} \lambda_{C,t_C-\nu+2} \mathcal{D}_{\theta^{-1}, \hat{\xi}_i}^{t_C-\nu+1}(x_r^{(i)}) \right) \\ &= \sum_{i=1}^{\ell} \sum_{r=1}^{\tau^{(i)}} \sigma_{FR}(a_r^{(i)})_{\hat{\xi}_i} \theta^{-(l-t_C-1)} (\mathcal{N}_{\theta}^{l-t_C-1}(\xi_i)) \cdot \theta^{-(l-t_C-1)} (\lambda_C(x_r^{(i)})_{\hat{\xi}_i}) = 0 \end{aligned}$$

where the second equality follows from

$$\mathcal{N}_{\theta^{-1}}^{l-\nu}(\tilde{\xi}_i) = \theta^{-(l-t_C-1)} (\mathcal{N}_{\theta^{-1}}^{t_C-\nu+1}(\tilde{\xi}_i) \cdot \mathcal{N}_{\theta}^{l-t_C-1}(\xi_i)). \quad (33)$$

Since $\sigma_F \cdot \sigma_R \cdot s \cdot \overline{\lambda_C} = \sigma_F \cdot s_{RC}$, the proof is complete. \blacksquare

For the ELP variant of the decoder, we exploit a different auxiliary syndrome $s_{CR} \in \mathbb{F}_{q^m}[x; \theta^{-1}]$. It is defined as

$$s_{CR}(x) = \lambda_C(x) \cdot \overline{s}(x) \cdot \mathbf{c}_{n-k-1}(\overline{\sigma_R}) \quad (34)$$

where $\mathbf{c}_{n-k-1}(\overline{\sigma_R}) := \theta^{n-k-1}(\overline{\sigma_R}(\theta^{-(n-k-1)}(x)))$ denotes the polynomial obtained from $\overline{\sigma_R}$ by applying θ^{n-k-1} to all its coefficients. Moreover, \overline{s} is the θ^{-1} -reverse of the syndrome polynomial s with respect to $n - k - 1$. We obtain the following key equation.

Theorem 2 (ELP Key Equation): There is a $\psi \in \mathbb{F}_{q^m}[x; \theta^{-1}]$ having degree less than $\tau = t_F + t_R + t_C$ that satisfies

$$\lambda_F(x) \cdot s_{CR}(x) \equiv \psi(x) \pmod{x^{n-k}}. \quad (35)$$

Sketch of Proof: Let us write $\lambda_{FC} := \lambda_F \cdot \lambda_C$ and compute

$$(\lambda_{FC} \cdot \overline{s})_l = \sum_{i=1}^{\ell} \sum_{r=1}^{\tau^{(i)}} \lambda_{FC}(x_r^{(i)})_{\theta^{-1}(\xi_i)} \mathcal{D}_{\theta, \xi_i}^{n-k-l}(a_r^{(i)}) \quad (36)$$

for $t_F + t_C + 1 \leq l \leq n - k$. Similar to the ESP variant, we can exploit that $\sigma_R(a_r^{(i)})_{\theta^{-1}(\xi_i^{-1})} = 0$ and finally obtain $(\lambda_F \cdot s_{CR})_l = 0$ for all $l = t_R + 1, \dots, t_F + t_C + d - 1$. \blacksquare

Observe that both key equations can be expressed as a homogeneous system of $n - k - \tau$ linear equations in t_F variables. Similar arguments as in [27, p. 132] combined with [24, Thm. 1.3.7] imply that its coefficient matrix has full rank. Hence, a unique solution exists if and only if $n - k - \tau \geq t_F$, that is if $2t_F + t_R + t_C \leq n - k$. As we will see shortly, this is the only necessary constraint on the number of errors and erasures and therefore the decoding radius of our decoder.

C. The Decoding Algorithm

Suppose we receive a vector $\mathbf{y} = \mathbf{c} + \mathbf{e} \in \mathbb{F}_q^n$ with $\text{wt}_{\Sigma R}(\mathbf{e}) = \tau = t_F + t_R + t_C$ along with the side-information \mathbf{a}_R for the t_R row erasures and \mathbf{B}_C for the t_C column erasures from the channel. Then our decoder proceeds as follows:

- 1) Compute the syndrome $\mathbf{s} = \mathbf{yH}^\top$ and the syndrome polynomial $s(x) = \sum_{l=1}^{n-k} s_l x^{l-1} \in \mathbb{F}_{q^m}[x; \theta^{-1}]$.
- 2) Compute the error locators $x_{C,j}^{(i)} = \sum_{\kappa=1}^{n_i} b_{C,j,\kappa}^{(i)} \alpha_{\kappa}^{(i)}$ for all $j = 1, \dots, t_C^{(i)}$.
- 3) Compute the skew polynomials

$$\lambda_C = \text{mpol}_{\{\theta^{-1}(\xi_i^{-1})\}_{i=1}^{\ell}}^{\{x_{C,j}^{(i)}\}_{j=1}^{t_C^{(i)}}} \quad \text{and} \quad \sigma_R = \text{mpol}_{\{\theta^{-1}(\xi_i^{-1})\}_{i=1}^{\ell}}^{\{a_{R,j}^{(i)}\}_{j=1}^{t_R^{(i)}}}.$$

- 4) Recover \mathbf{x} and \mathbf{a} by using one of the two variants:

ESP Variant

- a) Compute the auxiliary syndrome $s_{RC}(x) = \sigma_R(x) \cdot s(x) \cdot \overline{\lambda_C}(x)$.
- b) Recover σ_F by solving the ESP key equation (31).
- c) Find \mathbb{F}_q -linearly independent $a_{F,1}^{(i)}, \dots, a_{F,t_F^{(i)}}^{(i)}$ such that $\sigma_F(a_{F,j}^{(i)})_{\theta^{-1}(\xi_i^{-1})} = 0$ for all $j = 1, \dots, t_F^{(i)}$.
- d) Solve the LRS syndrome decoding problem (32) to get $(\sigma_F \cdot \sigma_R)(a_{C,j}^{(i)})_{\theta^{-1}(\xi_i^{-1})}$ for $j = 1, \dots, t_C^{(i)}$. Namely, solve $\hat{\mathbf{s}} = \hat{\mathbf{e}} \hat{\mathbf{H}}^\top$ with $\hat{\mathbf{H}} = \mathfrak{M}_{\theta^{-1}}^{n-k-t_F-t_R}(\hat{\alpha})_{\theta^{-1}(\xi)}$, where $\hat{\alpha}_r^{(i)} = \mathcal{D}_{\theta^{-1}, \theta^{-1}(\xi_i)}^{t_F+t_R-1}(x_r^{(i)})$ for $i = 1, \dots, \ell$ and

$r = 1, \dots, \tau^{(i)}$, and with \hat{e} having sum-rank weight at most t_C .

- e) Compute $\sigma_C = \text{mpol}_{\{(\sigma_F \cdot \sigma_R)(a_{C,j}^{(i)})_{\theta^{-1}(\xi_i^{-1})}\}_{j=1}^{t_C^{(i)}}}$ and $\sigma = \sigma_C \cdot \sigma_F \cdot \sigma_R$.
- f) Find \mathbb{F}_q -linearly independent $a_1^{(i)}, \dots, a_{\tau^{(i)}}^{(i)}$ such that $\sigma(a_r^{(i)})_{\theta^{-1}(\xi_i^{-1})} = 0$ for all $r = 1, \dots, \tau^{(i)}$, and $i = 1, \dots, \ell$.
- g) Solve (22) for x .

ELP Variant

- a) Compute $s_{CR}(x) = \lambda_C(x) \cdot \overline{s}(x) \cdot c_{n-k-1}(\overline{\sigma_R})$.
- b) Recover λ_F by solving the ELP key equation (35).
- c) Find \mathbb{F}_q -linearly independent $x_{F,1}^{(i)}, \dots, x_{F,t_F^{(i)}}^{(i)}$ such that $\lambda_F(x_{F,j}^{(i)})_{\theta^{-1}(\xi_i)} = 0$ for all $j = 1, \dots, t_F^{(i)}$ and $i = 1, \dots, \ell$.
- d) Solve the LRS syndrome decoding problem (36) to obtain $(\lambda_F \cdot \lambda_C)(x_{R,j}^{(i)})_{\theta^{-1}(\xi_i^{-1})}$ for all $i = 1, \dots, \ell$ and $j = 1, \dots, t_R^{(i)}$.
- e) Compute $\lambda_R = \text{mpol}_{\{(\lambda_F \cdot \lambda_C)(x_{R,j}^{(i)})_{\theta^{-1}(\xi_i)}\}_{j=1}^{t_R^{(i)}}}$ and $\lambda = \lambda_R \cdot \lambda_F \cdot \lambda_C$.
- f) Find \mathbb{F}_q -linearly independent $x_1^{(i)}, \dots, x_{\tau^{(i)}}^{(i)}$ such that $\lambda(x_r^{(i)})_{\theta^{-1}(\xi_i)} = 0$ for all $r = 1, \dots, \tau^{(i)}$ and $i = 1, \dots, \ell$.
- g) Solve (20) for a .
- 5) Recover $B_T^{(i)}$ from $x_T^{(i)}$ for $T \in \{F, R\}$ and $i = 1, \dots, \ell$. Namely, compute the j -th row of $B_T^{(i)}$ using a left inverse of the \mathbb{F}_q -expansion of $\alpha^{(i)}$ and the expansion of $x_{T,j}^{(i)}$ for $T \in \{F, R\}$, $i = 1, \dots, \ell$, and $j = 1, \dots, t_T^{(i)}$.
- 6) Compute $e = a_F \cdot B_F + a_R \cdot B_R + a_C \cdot B_C$ and return $c = y - e$.

The complexity-dominating tasks in the proposed error-erasure decoding algorithm can be accomplished as follows. All involved minimal polynomials have at most n roots and can hence be computed recursively in $\mathcal{O}(n^2)$ operations in \mathbb{F}_{q^m} using (11). The key equations (31) and (35) as well as the systems (20) and (22) can be solved via skew feedback shift register synthesis with complexity $\mathcal{O}((n-k)^2)$ [28]. The appearing syndrome decoding problems can be solved e.g. with a generalized version of Gabidulin's rank-metric decoder from [29, Sec. 6], which we will present in detail in an extended version of this paper, and complexity $\mathcal{O}(\tau^2)$. The root spaces of a skew polynomial $f \in \mathbb{F}_{q^m}[x; \theta]$ with respect to different evaluation parameters a_1, \dots, a_ℓ are uniquely determined according to [24, Prop. 1.3.7]. Bases for these root spaces can be computed by using the method from [30, Chap. 11.1] for each evaluation parameter, requiring at most $\mathcal{O}(n^3)$ operations in \mathbb{F}_q or $\mathcal{O}(n^2)$ operations in \mathbb{F}_{q^m} , respectively. Overall, the proposed error-erasure decoder has complexity $\mathcal{O}(n^2)$ operations in \mathbb{F}_{q^m} .

Theorem 3 (Error-Erasure Decoding): Consider an LRS code $\text{LRS}[\theta, \beta, \xi, \ell; n, k]$. If the number of full errors t_F , of row erasures t_R and of column erasures t_C satisfies $2t_F + t_R + t_C \leq n - k$, then the proposed decoder can recover the transmitted codeword requiring at most $\mathcal{O}(n^2)$ operations in \mathbb{F}_{q^m} .

We verified the results for the proposed error-erasure decoder by a proof-of-concept implementation in SageMath [31].

IV. APPLICATIONS

In [18] and [19] it was shown that the decoding problem for constant-dimension codes in the subspace metric can be cast to an error and row/column erasure decoding problem in the rank metric. By combining the ideas from [9], [18] and [19], our error-erasure decoder can be used to decode *lifted* LRS codes for error control in (noncoherent) multishot random linear network coding with respect to the sum-subspace metric [32]. For an LRS code $\mathcal{C} = \text{LRS}[\theta, \beta, \xi, \ell; n, k]$ the *lifted* LRS code $\mathcal{I}(\mathcal{C})$ consists of all lifted codewords obtained by blockwise application of the lifting operation from [19, Def. 3] (see [19]). Namely, the lifting of $c = (c^{(1)} \mid \dots \mid c^{(\ell)}) \in \mathcal{C}$ is given by

$$\mathcal{I}(c) := \left(\langle (I_{n_1}, C^{(1)\top}) \rangle_{\mathbb{F}_q}, \dots, \langle (I_{n_\ell}, C^{(\ell)\top}) \rangle_{\mathbb{F}_q} \right) \quad (37)$$

where $C^{(i)} \in \mathbb{F}_q^{m \times n_i}$ is the expansion of $c^{(i)} \in \mathbb{F}_{q^m}^{n_i}$ over \mathbb{F}_q for all $i = 1, \dots, \ell$ and $\langle \cdot \rangle_{\mathbb{F}_q}$ denotes the \mathbb{F}_q -linear row space of a matrix. After the transmission of a tuple $\mathcal{V} = (\mathcal{V}^{(1)}, \dots, \mathcal{V}^{(\ell)}) \in \mathcal{I}(\mathcal{C})$ over a multishot operator channel [32] with overall $\gamma = \sum_{i=1}^{\ell} \gamma^{(i)}$ insertions and $\delta = \sum_{i=1}^{\ell} \delta^{(i)}$ deletions we receive a tuple $\mathcal{U} = (\mathcal{U}^{(1)}, \dots, \mathcal{U}^{(\ell)})$. By applying the reduction [19, Def. 4] to each received component space $\mathcal{U}^{(i)}$ we get $Y^{(i)} = C^{(i)} + E^{(i)} \in \mathbb{F}_q^{m \times n_i}$ where $E^{(i)}$ can be decomposed with respect to the different error types as described in Section III-A and has \mathbb{F}_q -rank $\tau^{(i)} = t_F^{(i)} + t_R^{(i)} + t_C^{(i)}$. Therefore, the decoding problem for lifted LRS codes in the sum-subspace metric reduces to an error and row/column erasure decoding problem in the sum-rank metric, which can be solved by the proposed decoder. Similar as for one-shot subspace codes we have that $\gamma^{(i)} = t_F^{(i)} + t_R^{(i)}$ and $\delta^{(i)} = t_F^{(i)} + t_C^{(i)}$ (see e.g. [33]) where $t_C^{(i)}$ is also referred to as the number of *erasures* and $t_R^{(i)}$ is also referred to as the number of *deviations* (see [18], [19]).

Thus, the proposed decoder can correct an overall number of insertions and deletions up to $\gamma + \delta \leq n - k$, which coincides with the decoding region of the decoders from [9], [12] and [13].

Other applications of the presented error-erasure decoder include e.g. generalized minimum distance (GMD)-inspired randomized decoding algorithms for cryptography (see e.g. [34], [35]) as well as error-erasure decoding problems in the sum-rank metric arising in any context.

V. CONCLUSION

We presented a Berlekamp–Massey-like error-erasure decoder for linearized Reed–Solomon (LRS) codes that can correct t_F full errors, t_R row erasures and t_C column erasures up to $2t_F + t_R + t_C \leq n - k$ in the sum-rank metric, where n is the code length and k is the code dimension. The proposed decoder requires at most $\mathcal{O}(n^2)$ operations in \mathbb{F}_{q^m} and, up to our knowledge, is the first scheme for LRS codes capable of correcting both errors and erasures in the sum-rank metric. We showed how the proposed decoder can be used for error control in noncoherent multishot network coding. Future work will include error-erasure decoding of interleaved LRS codes and consider the implications of errors and erasures in the *skew metric*, which is isomorphic to the sum-rank metric.

REFERENCES

- [1] H.-F. Lu and P. V. Kumar, "A Unified Construction of Space-Time Codes with Optimal Rate-Diversity Tradeoff," *IEEE Transactions on Information Theory*, vol. 51, no. 5, pp. 1709–1730, 2005.
- [2] R. W. Nóbrega and B. F. Uchôa-Filho, "Multishot Codes for Network Coding using Rank-Metric Codes," in *2010 Third IEEE International Workshop on Wireless Network Coding*. IEEE, 2010, pp. 1–6.
- [3] A. Wachter, V. R. Sidorenko, M. Bossert, and V. V. Zyablov, "On (Partial) Unit Memory Codes Based on Gabidulin Codes," *Problems of Information Transmission*, vol. 47, no. 2, pp. 117–129, 2011.
- [4] A. Wachter-Zeh, M. Stinner, and V. Sidorenko, "Convolutional Codes in Rank Metric with Application to Random Network Coding," *IEEE Transactions on Information Theory*, vol. 61, no. 6, pp. 3199–3213, 2015.
- [5] D. Napp, R. Pinto, J. Rosenthal, and P. Vettori, "MRD Rank Metric Convolutional Codes," in *IEEE International Symposium on Information Theory (ISIT)*. IEEE, 2017, pp. 2766–2770.
- [6] —, "Faster Decoding of Rank Metric Convolutional Codes," in *23rd International Symposium on Mathematical Theory of Networks and Systems*, 2018, pp. 507–510.
- [7] E. Byrne, H. Gluesing-Luerssen, and A. Ravagnani, "Fundamental Properties of Sum-Rank-Metric Codes," *IEEE Transactions on Information Theory*, vol. 67, no. 10, pp. 6456–6475, 2021.
- [8] U. Martínez-Peñas, "Skew and Linearized Reed–Solomon Codes and Maximum Sum Rank Distance Codes over any Division Ring," *Journal of Algebra*, vol. 504, pp. 587–612, 2018.
- [9] U. Martínez-Peñas and F. R. Kschischang, "Reliable and Secure Multishot Network Coding Using Linearized Reed–Solomon Codes," *IEEE Transactions on Information Theory*, vol. 65, no. 8, pp. 4785–4803, 2019.
- [10] —, "Universal and Dynamic Locally Repairable Codes with Maximal Recoverability via Sum-Rank Codes," *IEEE Transactions on Information Theory*, vol. 65, no. 12, pp. 7790–7805, 2019.
- [11] S. Puchinger, J. Renner, and J. Rosenkilde, "Generic Decoding in the Sum-Rank Metric," in *2020 IEEE International Symposium on Information Theory (ISIT)*. IEEE, 2020, pp. 54–59.
- [12] H. Bartz and S. Puchinger, "Decoding of Interleaved Linearized Reed–Solomon Codes with Applications to Network Coding," in *IEEE International Symposium on Information Theory (ISIT)*. IEEE, 2021, pp. 160–165.
- [13] —, "Fast Decoding of Interleaved Linearized Reed–Solomon Codes and Variants," *submitted to: IEEE Transactions on Information Theory*, 2022, available at <https://arxiv.org/abs/2201.01339>.
- [14] F. Hörmann and H. Bartz, "Efficient Decoding of Folded Linearized Reed–Solomon Codes in the Sum-Rank Metric," in *The Twelfth International Workshop on Coding and Cryptography (WCC)*, 2022, available at <https://arxiv.org/abs/2109.14943>.
- [15] E. M. Gabidulin, A. V. Paramonov, and O. V. Tretjakov, "Rank Errors and Rank Erasures Correction," in *4th International Colloquium on Coding Theory*, 1991, pp. 11–19.
- [16] S. Puchinger and U. Martínez-Peñas, Personal Communication, 2021, to appear in an extended version of arXiv:2109.09551.
- [17] G. Richter and S. Plass, "Error and Erasure Decoding of Rank-Codes with a Modified Berlekamp–Massey Algorithm," in *5th International ITG Conference on Source and Channel Coding (SCC)*, Erlangen, 2004, pp. 203–210.
- [18] D. Silva, "Error Control for Network Coding," Ph.D. dissertation, University of Toronto, 2009.
- [19] D. Silva, F. R. Kschischang, and R. Kötter, "A Rank-Metric Approach to Error Control in Random Network Coding," *IEEE Transactions on Information Theory*, vol. 54, no. 9, pp. 3951–3967, 2008.
- [20] T.-Y. Lam and A. Leroy, "Vandermonde and Wronskian Matrices over Division Rings," *Journal of Algebra*, vol. 119, no. 2, pp. 308–336, 1988.
- [21] W. Li, V. Sidorenko, and D. Silva, "On Transform-Domain Error and Erasure Correction by Gabidulin Codes," *Designs, Codes and Cryptography*, vol. 73, no. 2, pp. 571–586, 2014.
- [22] A. Leroy, "Pseudo Linear Transformations and Evaluation in Ore Extensions," *Bulletin of the Belgian Mathematical Society-Simon Stevin*, vol. 2, no. 3, pp. 321–347, 1995.
- [23] U. Martínez-Peñas, "Private Information Retrieval from Locally Repairable Databases with Colluding Servers," in *IEEE International Symposium on Information Theory (ISIT)*. IEEE, 2019, pp. 1057–1061.
- [24] X. Caruso, "Residues of Skew Rational Functions and Linearized Goppa Codes," *arXiv preprint arXiv:1908.08430v1*, 2019.
- [25] X. Caruso and A. Durand, "Duals of Linearized Reed–Solomon Codes," *arXiv preprint arXiv:2110.12675*, 2021.
- [26] E. M. Gabidulin and N. I. Pilipchuk, "Error and Erasure Correcting Algorithms for Rank Codes," *Designs, Codes and Cryptography*, vol. 49, no. 1–3, pp. 105–122, 2008.
- [27] E. M. Gabidulin, "A Fast Matrix Decoding Algorithm for Rank-Error-Correcting Codes," in *Algebraic Coding*. Springer-Verlag, 1992, pp. 126–133.
- [28] V. R. Sidorenko, L. Jiang, and M. Bossert, "Skew-Feedback Shift-Register Synthesis and Decoding Interleaved Gabidulin Codes," *IEEE Transactions on Information Theory*, vol. 57, no. 2, pp. 621–632, 2011.
- [29] E. M. Gabidulin, "Theory of Codes with Maximum Rank Distance," *Problems of Information Transmission*, vol. 21, no. 1, pp. 1–12, 1985.
- [30] E. R. Berlekamp, *Algebraic Coding Theory (revised edition)*. World Scientific, 2015.
- [31] W. A. Stein *et al.*, SageMath Software, <http://www.sagemath.org>.
- [32] R. W. Nóbrega and B. F. Uchôa-Filho, "Multishot Codes for Network Coding: Bounds and a Multilevel Construction," in *2009 IEEE International Symposium on Information Theory (ISIT)*. IEEE, 2009, pp. 428–432.
- [33] H. Bartz, "Algebraic Decoding of Subspace and Rank-Metric Codes," Ph.D. dissertation, Technical University of Munich, 2017.
- [34] T. Jerkovits and H. Bartz, "Weak Keys in the Faure-Loidreau Cryptosystem," in *7th Code-Based Cryptography Workshop (CBC)*, Darmstadt, Germany, 2019, pp. 102–114.
- [35] J. Renner, T. Jerkovits, H. Bartz, S. Puchinger, P. Loidreau, and A. Wachter-Zeh, "Randomized Decoding of Gabidulin Codes Beyond the Unique Decoding Radius," in *11th International Conference on Post-Quantum Cryptography (PQCrypto)*, Paris, France, 2020, pp. 3–19.